



KATKO's AISI 316 stainless steel enclosed IP69K safety switches are protected against close-range high pressure, high temperature spray downs.

Available in 2 different enclosure sizes and with 3, 4, 6 or 8 poles. 3 and 4 poles up to 125 A and 6 and 8 poles up to 80 A.

## STAINLESS STEEL Safety Switch 16 - 125 A

- IP69K/IP69 rating
- AISI 316
- Where hygiene and good protection against corrosion are required
- Padlockable

| Type           |                    | AC-22              | 400 V              | AC-23  | 400 V              | AC-23  | 690 V              | EAN code<br>6419410... |           | Enclosure | Weight |
|----------------|--------------------|--------------------|--------------------|--------|--------------------|--------|--------------------|------------------------|-----------|-----------|--------|
|                |                    |                    | 415 V              |        |                    |        |                    |                        |           |           |        |
|                |                    |                    | 690 V              |        | 415 V              |        |                    |                        |           |           |        |
| G/B            | Y/R                | I <sub>n</sub> / A | I <sub>n</sub> / A | P / kW | I <sub>n</sub> / A | P / kW | I <sub>n</sub> / A | G/B                    | Y/R       |           | kg     |
| <b>3 poles</b> |                    |                    |                    |        |                    |        |                    |                        |           |           |        |
| KER 316 IP69K  | KER 316 Y/R IP69K  | 16 A               | 16 A               | 7.5 kW | 16 A               | 11 kW  | ...                | 325919                 | ...326152 | H23       | 1.2    |
| KER 325 IP69K  | KER 325 Y/R IP69K  | 25 A               | 25 A               | 11 kW  | 25 A               | 22 kW  | ...                | 325926                 | ...326169 | H23       | 1.2    |
| KER 340 IP69K  | KER 340 Y/R IP69K  | 40 A               | 40 A               | 22 kW  | 32 A               | 30 kW  | ...                | 325933                 | ...326176 | H23       | 1.2    |
| KER 363 IP69K  | KER 363 Y/R IP69K  | 63 A               | 40 A               | 22 kW  | 40 A               | 37 kW  | ...                | 325940                 | ...326183 | H32       | 2.3    |
| KER 380 IP69K  | KER 380 Y/R IP69K  | 80 A               | 63 A               | 30 kW  | 40 A               | 37 kW  | ...                | 325957                 | ...326190 | H32       | 2.3    |
| KER 3100 IP69K | KER 3100 Y/R IP69K | 100 A              | 80 A               | 45 kW  | 63 A               | 55 kW  | ...                | 325964                 | ...326206 | H32       | 6.9    |
| KER 3125 IP69K | KER 3125 Y/R IP69K | 125 A              | 125 A              | 55 kW  | 80 A               | 75 kW  | ...                | 325971                 | ...326213 | H32       | 6.9    |
| <b>4 poles</b> |                    |                    |                    |        |                    |        |                    |                        |           |           |        |
| KER 416 IP69K  | KER 416 Y/R IP69K  | 16 A               | 16 A               | 7.5 kW | 16 A               | 11 kW  | ...                | 325988                 | ...326220 | H23       | 1.3    |
| KER 425 IP69K  | KER 425 Y/R IP69K  | 25 A               | 25 A               | 11 kW  | 25 A               | 22 kW  | ...                | 325995                 | ...326237 | H23       | 1.3    |
| KER 440 IP69K  | KER 440 Y/R IP69K  | 40 A               | 40 A               | 22 kW  | 32 A               | 30 kW  | ...                | 326008                 | ...326244 | H23       | 1.3    |
| KER 463 IP69K  | KER 463 Y/R IP69K  | 63 A               | 40 A               | 22 kW  | 40 A               | 37 kW  | ...                | 326015                 | ...326251 | H32       | 2.4    |
| KER 480 IP69K  | KER 480 Y/R IP69K  | 80 A               | 63 A               | 30 kW  | 40 A               | 37 kW  | ...                | 326022                 | ...326268 | H32       | 2.4    |
| KER 4100 IP69K | KER 4100 Y/R IP69K | 100 A              | 80 A               | 45 kW  | 63 A               | 55 kW  | ...                | 326039                 | ...326275 | H32       | 7      |
| KER 4125 IP69K | KER 4125 Y/R IP69K | 125 A              | 125 A              | 55 kW  | 80 A               | 75 kW  | ...                | 326046                 | ...326282 | H32       | 7      |
| <b>6 poles</b> |                    |                    |                    |        |                    |        |                    |                        |           |           |        |
| KER 616 IP69K  | KER 616 Y/R IP69K  | 16 A               | 16 A               | 7.5 kW | 16 A               | 11 kW  | ...                | 326053                 | ...326299 | H32       | 1.3    |
| KER 625 IP69K  | KER 625 Y/R IP69K  | 25 A               | 25 A               | 11 kW  | 25 A               | 22 kW  | ...                | 326060                 | ...326305 | H32       | 1.3    |
| KER 640 IP69K  | KER 640 Y/R IP69K  | 40 A               | 40 A               | 22 kW  | 32 A               | 30 kW  | ...                | 326077                 | ...326312 | H32       | 1.3    |
| KER 663 IP69K  | KER 663 Y/R IP69K  | 63 A               | 40 A               | 22 kW  | 40 A               | 37 kW  | ...                | 326084                 | ...326329 | H32       | 2.4    |
| KER 680 IP69K  | KER 680 Y/R IP69K  | 80 A               | 63 A               | 30 kW  | 40 A               | 37 kW  | ...                | 326091                 | ...326336 | H32       | 2.4    |
| <b>8 poles</b> |                    |                    |                    |        |                    |        |                    |                        |           |           |        |
| KER 816 IP69K  | KER 816 Y/R IP69K  | 16 A               | 16 A               | 7.5 kW | 16 A               | 11 kW  | ...                | 326107                 | ...326343 | H32       | 1.3    |
| KER 825 IP69K  | KER 825 Y/R IP69K  | 25 A               | 25 A               | 11 kW  | 25 A               | 22 kW  | ...                | 326114                 | ...326350 | H32       | 1.3    |
| KER 840 IP69K  | KER 840 Y/R IP69K  | 40 A               | 40 A               | 22 kW  | 32 A               | 30 kW  | ...                | 326121                 | ...326367 | H32       | 1.3    |
| KER 863 IP69K  | KER 863 Y/R IP69K  | 63 A               | 40 A               | 22 kW  | 40 A               | 37 kW  | ...                | 326138                 | ...326374 | H32       | 2.4    |
| KER 880 IP69K  | KER 880 Y/R IP69K  | 80 A               | 63 A               | 30 kW  | 40 A               | 37 kW  | ...                | 326145                 | ...326381 | H32       | 2.4    |